

Battery Charger TC200-EX

Owner's Manual

Introduction

The TC200-EX Battery Charger is electrically compatible with BP-U90/U60/U30 batteries.

Standard Features

- Two simultaneous charge positions for fast charging of 2 batteries.
- Fast, safe, and reliable charging. The battery pack can be left on the charger after the charge is complete.
- Dynamic Power Management (DPM) minimizes battery charge time. By dynamically adjusting battery charge current, more current is allocated to the deeper discharged battery. Through this process all batteries are ready to use at about the same time.
- Wide range input power compatibility (100-240VAC 50-60Hz).
- Compact, lightweight design for easy portability.

Batteries

The charger is capable of charging 2 batteries at the same time. It accepts Sony BP-U90/U60/U30 style batteries. The charger is also compatible with non-OEM batteries.

Charging time

The time to full charge depends on the battery pack rated capacity, its state of charge prior to insertion, and its age. A fully discharged new BP-U60 battery will be fully charged (more than 90%) in about 4 hours (4.5 -6 hours when 2 batteries are being charged). Since a depleted battery pack absorbs charge current faster, than a partially charged one, most of the charge energy is absorbed during the initial stage of charging and then the rate of charge levels off towards the end.

Charge channels

LEDs indicate each battery's state of charge. Dynamic Power Management (DPM) minimizes battery charge time. By dynamically adjusting battery charge current, more current is allocated to the deeper discharged of the two batteries. Through this process both batteries are ready to use at about the same time

Operation

Charging

Operation of the charger is fully automatic. Upon plugging the charger in into an electrical source the green and red LEDs will blink every 3 seconds to indicate the charger is powered on. Mount a battery to an open position on the charger and the charger will initiate the charge routine. While charging is in progress, the red LED will illuminate. Approaching charge completion, the Green LED will blink at 75%/90% readiness level, and will be steady ON on completion.

Status LEDs

- | | |
|---------------------------|---|
| 1. Red ON | Battery is inserted; charge in progress |
| 2. Green blinking (short) | Battery is charged over 75% |
| 3. Green blinking | Battery is charged over 90% |
| 4. Green ON | Ready |