

Battery Charger TC200-DSLR-C

Owner's Manual

Introduction

The TC200-DSLR-C Battery Charger is electrically compatible with Canon LP-E6 batteries. With the appropriate power cord, the charger can be powered by a 12V automobile power source.

Standard Features

- Two simultaneous charge positions for fast charging of 2 batteries.
- Fast, safe, and reliable charging. The battery pack can be left on the charger after the charge is complete.
- Dynamic Power Management (DPM) minimizes battery charge time. By dynamically adjusting battery charge current, more current is allocated to the deeper discharged of the two batteries. Through this process both batteries are ready to use at about the same time.
- Wide range input power compatibility (100-240VAC 50-60Hz), 12V with the DC cigarette lighter cord.
- Compact, lightweight design for easy portability. Dimensions 5.5"x 4"x 1.5"

Batteries

The charger is capable of charging 2 batteries at the same time. It accepts Canon LP-E6 style batteries.

Charging time

The time to full charge depends on the battery pack rated capacity, its state of charge prior to insertion, and its age. A fully discharged new battery pack will be fully charged (more than 90%) in about 2 hours. Since a depleted battery pack absorbs charge current faster than a partially charged one, most of the charge energy is absorbed during the initial stage of charging and then the rate of charge levels off towards the end.

Charge channels

Both charge channels are independent from each other; charge initiation and termination depend on a battery's state of charge. LEDs indicate each battery's state of charge. Dynamic Power Management (DPM) minimizes battery charge time. By dynamically adjusting battery charge current, more current is allocated to the deeper discharged of the two batteries. Through this process both batteries are ready to use at about the same time

Operation

Charging

Operation of the charger is fully automatic. Upon plugging the charger in into an electrical source the green and red LEDs will blink every 3 seconds to indicate the charger is powered on. Mount a battery to an open position on the charger and the charger will initiate the charge routine. While charging is in progress, the red LED will illuminate. Approaching charge completion, the Green LED will blink at 90% readiness level, and will be steady ON on completion.

Status LEDs

- | | | | |
|-------------------|---|-------------|-------|
| 1. Red ON | Battery is inserted; charge in progress | 3. Green ON | Ready |
| 2. Green blinking | Battery is charged over 90% | | |